

S90...W Contrast sensor

INSTRUCTION MANUAL

CONTROLS

OUTPUT LED

The yellow LED ON indicates that the N.O. (normally open) output status is closed.

READY/ERROR LED (bicolour)

When the bicoloured LED is continuously green, the sensor is operating in a normal condition and it is ready to function correctly (stability condition).

The red and green blinking of the LED indicates a wrong sensor setting. Please refer to the "SETTING" paragraph to get the correct setting procedure.

SET PUSHBUTTON

A long pressure on the pushbutton activates the self-setting procedure. The REMOTE input allows the external control of the SET pushbutton.

INSTALLATION

The sensor can be positioned by means of the housing's holes using two screws (M4x25 or longer, 1.5 Nm maximum tightening torque) with washers.

Various orientable fixing brackets to ease the sensor positioning are available (please refer to the accessories listed in the general catalogue).

The operating distance is measured from the front surface of the sensor optics. The M12 connector can be oriented at four different positions rotating the block of 0°, 90°, 180° or 270°.

CONNECTIONS

M12 CONNECTOR



* = Connect the REMOTE wire to 0 V if not used.

NOTE

If a setting error will occur please repeat again the EASY TOUCH $^{\rm IM}$ setting procedure, in order to be sure to restart the setting procedure correctly.





0

6

<u>.</u>



TECHNICAL DATA

mm

Power supply:	10 30 Vdc (limit values)
Ripple:	2 Vpp max.
Current consumption (output current excluded):	30 mA max.
Outputs:	PNP or NPN; 30 Vdc max. (short-circuit protection)
Output current:	100 mA
Output saturation voltage:	≤ 2 V
Response time:	100 µs max.
Switching frequency:	5 kHz
Indicators:	OUTPUT LED (YELLOW) / READY/ERROR LED (GREEN/RED)
Setting:	SET pushbutton
Data retention:	non volatile EEPROM memory
Operating temperature:	-10 55 °C
Storage temperature:	-20 70 °C
Electrical shock protection:	Class 2, double insulation
Operating distance (typical values):	19 mm ±2 mm
Minimum spot dimension:	3.5 mm at 19 mm
Emission type:	white light LED (400-700 nm)
Ambient light rejection:	according to EN 60947-5-2
Vibrations:	0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6)
Shock resistance:	11 ms (30 G) 6 shock for every axis (EN60068-2-27)
DARK/LIGHT selection:	DARK mode with EASY TOUCH™ / Automatic with fine detection
Housing:	ZAMA
Lens:	glass window (skewed anti-reflection); glass lens
Mechanical protection:	IP67 (TYPE 1 ENCLOSURE)
Connections:	M12-4 pole connector
Weight:	77 g.

DELAY FUNCTION

Press the SET pushbutton and keep it pressed until the READY/ERROR LED turns off, blinking and turns off again, then release the SET pushbutton.

If the delay function is not active the READY/ERROR LED blinks green with 2 quick pulses.

If the delay function is active the READY/ERROR LED blinks green with 4 quick pulses.

Press and release immediately the SET pushbutton in order to change the function status, the new function status is indicated the READY/ERROR LED as the mode before described. The delay function adds 20ms to the duration of the sensor's ON pulse.

SETTING

EASY TOUCH™

The sensor uses the patent-covered EASY TOUCH™ technology that allows a rapid and safe self-setting of the product. Two different setting possibilities are available:

- EASY TOUCH TM; a long pressure of the SET pushbutton allows selfsetting.
- FINE DETECTION; to be used only in particularly critical conditions. This setting procedure is used only when the EASY TOUCH[™] is not sufficient.

S90...W setting

To achieve a correct sensor functioning, the coloured mark or object to be detected has to be placed at the right reading distance.

EASY TOUCH™ (standard detection in the DARK mode)

The EASY TOUCH™ technology allows the functioning in the DARK mode (mark presents a lower light intensity respect to the background).

The mark to detect has to be placed correctly at the right reading distance within the sensor spot.

Press the SET pushbutton until the READY/ERROR LED turns off. Release the SET pushbutton and wait for the READY/ERROR LED to turn green

The sensor is now ready to detect the pre-set coloured mark or object (output LED turns on when the NO output is closed).

Fine detection (DARK or LIGHT mode)

This mode offers an improved detection precision. The sensor can function either in the DARK operating or in the LIGHT operating mode (light-coloured mark on dark background).

The operating mode is selected automatically by the sensor.

The mark to detect has to be placed correctly at the right reading distance within the sensor spot.

Press the SET pushbutton. The READY/ERROR LED turns off. Keep the SET pushbutton pressed until the READY/ERROR LED blinks green. Place the background under the sensor spot.

Press the SET pushbutton again until the READY/ERROR LED turns off.

The sensor is now ready to detect, with a very high precision, the preset coloured mark (output LED turns on, READY/ERROR LED turns areen).

The output LED is ON and the NO output is closed, when the sensor is positioned on the pre-set coloured mark.

REMOTE FUNCTION

The REMOTE wire, if connected to +Vdc, is equal to the pressure of the SET button. If the REMOTE wire is connected to +Vdc, when the sensor is powered ON, the <u>keyboard lock</u> function is activated; the SET button is no longer active. To deactivate the <u>keyboard lock</u> function, the sensor has to be turned off and powered again with the REMOTE wire not connected to OV.

DECLARATION OF CONFORMITY

We DATALOGIC AUTOMATION declare under our sole responsibility that these products are conform to the 2004/108/CE and successive amendments.

WARRANTY

DATALOGIC AUTOMATION warrants its products to be free from defects.

DATALOGIC AUTOMATION will repair or replace, free of charge, any product found to be defective during the warranty period of 36 months from the manufacturing date.

This warranty does not cover damage or liability deriving from the improper application of DATALOGIC AUTOMATION products.

DATALOGIC AUTOMATION

Via Lavino 265 - 40050 Monte S.Pietro - Bologna – Italy Tel: +39 051 6765611 - Fax: +39 051 6759324 www.automation.datalogic.com e-mail:info.automation.it@datalogic.com

DATALOGIC AUTOMATION cares for the environment: 100% recycled paper. DATALOGIC AUTOMATION reserves the right to make modifications and improvements without prior notification.

Datalogic and the Datalogic logo are registered trademarks of Datalogic S.p.A. in many countries, including the U.S.A. and the E.U.

826002101 Rev.C © Copyright Datalogic 2003-2009